

MINI ELLA PENDANT

PRODUCT FEATURES

- From the brand formerly known as Tech Lighting
- Elegant and sophisticated design
- As each piece is artisan made, slight variations are an inherent part of this hand-blown glass fixture
- Ideal for kitchen islands, task lighting and vanity lighting
- Available lamping options include energy efficient LED or halogen
- Monopoint version - The LED Driver is housed within the junction box. (L. 3.05" | W. 1.5" | H. .98")



LAMPING

Includes low-voltage, 35 watt halogen bi-pin lamp and six feet of field-cuttable cable. Dimmable with low-voltage electronic or magnetic dimmer (based on the transformer).

Smoke



Clear

Smoke

ORDERING INFORMATION

700	SYSTEM	COLOR	FINISH	LAMP
	FJ FREEJACK	C CLEAR	Z ANTIQUE BRONZE	12 VOLT HALOGEN (T20)
	KL KABLE LITE	K SMOKE	S SATIN NICKEL	
	MP MONOPOINT			
	MO MONORAIL			

Note: MP includes 4" Round Flush Canopy.
Antique Bronze is not available for Kable Lite.

700

JOB NAME

NOTES




MINI ELLA PENDANT

elegant
lighting

SPECIFICATIONS

PRIMARY MATERIAL	Glass
SHADE MATERIAL	Glass
NET WEIGHT	2.5 lbs
HEIGHT	7in
WIDTH	5in
LENGTH	5in
UP LIGHT / DOWN LIGHT / BOTH?	
WET LISTED	
DAMP LISTED	
DRY LISTED	
MIN. HANGING HEIGHT	13.5in
MAX HANGING HEIGHT	79.5in
SLOPED CEILING ADAPTABLE?	Yes 45° Max
GENERAL LISTING	ETL Listed
INCLUDES	



LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP
DELIVERED LUMENS			360	
WATTS			35	
MAX WATTAGE PER BULB			35W	
			12V ELV, MLV	
			120V ELV, MLV	
CCT			3000K	
CRI			100 CRI	
LED LIFETIME				
L70				
AVERAGE BULB HOURS				
FIELD SERVICEABLE LED				
LAMP BASE			GY 6.35	
LAMP SHAPE			T4	
LAMP INCLUDED?			True	
WARRANTY**			1 Year	

T20 / T24 / JA8 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6 / JA8.			
This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California.			

* If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.